

## L@TITUDE NETWORK VISION ANNUNCIATOR



### STANDARD FEATURES

- Full-color 7" (800 x 480 pixel) interface
- Replicates information displayed at the FACP
- Automatic display brightness adjustment
- Internal buzzer
- Connects via control panel network terminals
- Low current, 24V DC powered
- Configurable functionality
- Enable key-switch
- Sheet steel enclosure
- Surface or semi-flush enclosure options available

### TECHNICAL SPECIFICATIONS

<b>Supply Voltage Range</b>	21-30V DC
<b>Quiescent Current during Power Failure</b>	216mA typical (buzzer off @ 24V DC) 246mA typical (buzzer on @ 24V DC) 341mA max (buzzer on @ 21V DC)
<b>Maximum Number of Units on a Network</b>	31 Annunciators
<b>Size</b>	9.25" x 6.7" x 2.2" (235mm x 170mm x 55mm)
<b>Display</b>	Full color 800 x 480 LCD with resistive touch screen and automatic back-light dimming
<b>Construction</b>	18 SWG, 1.2mm mild sheet steel
<b>Cable Entry</b>	2 x 20 mm knockouts on top & bottom 4 x 20 mm and 2 x 28 mm knock outs in back
<b>Vision Annunciator Electronics Only</b>	S787
<b>Finish</b>	Epoxy powder coated
<b>Color</b>	Enclosure ● Red (RAL3002) ● Gray (BS 00 A 05) ● Black (RAL9005)
	Fascia ○ Signal White (RAL9003)
<b>Optional Semi-Flush Mounting Collar Kit</b>	KM1098RD - Red KM1098GY - Gray KM1098BS - Black
<b>Weight</b>	4.4 lbs (2 kg) maximum
<b>IP Rating</b>	IP 30

### DESCRIPTION

The L@titude Network Vision Annunciator is the most qualified annunciator on the market. It is a full-color graphical display and touchscreen. It represents the most versatile annunciator for life safety systems available today. The Annunciator is a full-function fire alarm repeater that is configurable and application flexible for use in applications such as hospital nursing stations and elevator alarms.

L@titude Network Vision Annunciators can be configured to fully replicate fire control panel functionality, or to operate as simple, display-only devices for applications where access to fire alarm controls are inappropriate.

### PRODUCT LISTINGS



California State  
Fire Marshal  
7120-0410:0507

Manufactured by Kentec Electronics Ltd.  
Dartford, DA11JQ, United Kingdom

Specifications subject to change without notice.

Hochiki America Corporation  
7051 Village Drive, Suite 100, Buena Park, CA 90621-2268  
Phone: 714-522-2246 Fax: 714-522-2268  
Technical Support: 800-845-6692 or technicalsupport@hochiki.com



Find latest revision at [www.hochiki.com](http://www.hochiki.com)